



LED Emergency Conversion Kit



vootu
LED EMERGENCY CONVERSION KIT

 Type: EMI-22-1T
 Input: 110-277V, 50/60 Hz
 Emergency Output: 220V
 Lamp: 22W LED Tube
 Charge Time: 24 hours
 Discharge Time: 1.5 hours
 Battery: Ni-Cd 12V 3.5AH
 To 85°C max

Vootu/UL Part #	Lamp	Input	Emergency Output	Charge Time	Discharge Time	Battery	Dimensions
VT-TR-EMERG	22W LED Tube Max	110-277V	220V	24 hours	1.5 hours	Ni-Cd 12V 3.5AH	17x5x2"

Product Description:

LED Emergency Conversion Kit can be easily installed into the fixture to power (1) LED emergency light source. It is equipped with a high temperature Ni-CD 12V battery pack.

Warning for installation for ballast compatible tube:

1. A test is required before making mass installation.
2. Make sure the socket and lampholder of the fixture are not loose or damaged
3. Make sure that you turn off power before making installation.
4. Make sure that the length of the tube is suitable for the fixture
5. This tube only works with specific electronic ballast, not all ballasts. **Do not connect this ballast compatible tube with magnetic ballast.**
6. This ballast compatible tube may not work with all ballasts because the ballast may be special or old.