



T8 Tube – 4ft 18w Hybrid Ballast Compatible



RoHS

DE=Dual ended, SE=Single Ended, MS=Micro Switch, HY=Hybrid

Vootu/UL Part #	Size	Watts	Lumens	CRI	CCT	Voltage	Pwr Type	Dimensions	Beam Angle	IP	Base
VT-T812-18WF04 4K	4'	18	2025	>80	4000k	100-277	HY	1206mm	120	20	G13
VT-T812-18WF04 5K	4'	18	2087	>80	5000k	100-277	HY	1206mm	120	20	G13

Product Description:

18 watt – 4ft. retrofit T8 tube replaces traditional 32 watt tube. Dual Ended Power with frosted cover. **Please note: Direct Replacement for 32w 4' T8 Lamps Only. No wiring or tombstone modification is required.**



E478735

11721 US Highway 19 N. • Clearwater, FL 33764 • (727) 314-8656

May 4, 2017

Warning for installation for ballast compatible tube:

1. A test is required before making mass installation.
2. Make sure the socket and lampholder of the fixture are not loose or damaged
3. Make sure that you turn off power before making installation.
4. Make sure that the length of the tube is suitable for the fixture
5. This tube only works with specific electronic ballast, not all ballasts. **Do not connect this ballast compatible tube with magnetic ballast.**
6. This ballast compatible tube may not work with all ballasts because the ballast may be special or old.